

**BLAKELY, SOKOLOFF, TAYLOR & ZAFMAN LLP**  
12400 Wilshire Blvd., 7th Floor  
Los Angeles, CA 90025-1026  
(714) 557-3800

THE UNIVERSITY OF CHICAGO

-1-

## **BRIEF DESCRIPTION OF THE DRAWINGS**

[0006] The features and advantages of the present invention will become apparent from the following detailed description of the present invention in which:

[0007] Figure 1 is a diagram illustrating a system in which one embodiment of the invention can be practiced.

[0008] Figure 2 is a diagram illustrating a base-band circuit shown in Figure 1 according to one embodiment of the invention.

[0009] Figure 3 is a diagram illustrating a multiplier-free demodulator shown in Figure 2 according to one embodiment of the invention.

[0010] Figure 4 is a diagram illustrating a low power passive correlator shown in Figure 2 according to one embodiment of the invention.

[0011] Figure 5 is a diagram illustrating a correlator circuit shown in Figure 4 according to one embodiment of the invention.

[0012] Figure 6 is a diagram illustrating the synchronous operation between the circularly shifted data register and the code register shown in Figure 4 according to one embodiment of the invention.

[0013] Figure 7A is a diagram illustrating a range of correlation result using the actual ranges according to one embodiment of the invention.

[0014] Figure 7B is a diagram illustrating a range of correlation result using the represented ranges according to one embodiment of the invention.

[0015] Figure 7C is a diagram illustrating a mapping of the correlation result according to one embodiment of the invention.

[0016] Figure 8A is a diagram illustrating a pseudo random number generator and re-tracking circuit shown in Figure 2 according to one embodiment of the invention.

[0017] Figure 8B is a diagram illustrating a PN code generator shown in Figure 8A according to one embodiment of the invention.

[0018] Figure 8C is a diagram illustrating a tap selector shown in Figure 8B according to one embodiment of the invention.

[0019] Figure 9 is a diagram illustrating a control circuit for PN shifting according to one embodiment of the invention.

[0020] Figure 10 is a diagram illustrating PV shifting technique as it applies to one code NCO generator according to one embodiment of the invention.

[0021] Figure 11A is a diagram illustrating a Doppler circuit shown in Figure 2 according to one embodiment of the invention.

[0022] Figure 11B is a diagram illustrating a carrier NCO base circuit shown in Figure 2 according to one embodiment of the invention.

[0023] Figure 12 is a diagram illustrating a mixer circuit shown in Figure 11 according to one embodiment of the invention.

[0024] Figure 13 is a diagram illustrating an epoch processing circuit shown in Figure 2, which controls the I and Q memory circuits according to one embodiment of the invention.

[0025] Figure 14 is a diagram illustrating a memory circuit shown in Figure 13 according to one embodiment of the invention.

### **DESCRIPTION**

[0026] In the following description, for purposes of explanation, numerous details are set forth in order to provide a thorough understanding of the present invention. However, it will be apparent to one skilled in the art that these specific details are not required in order to practice the present invention. In other

instances, well-known electrical structures and circuits are shown in block diagram form in order not to obscure the present invention.

[0027] One embodiment of the present invention includes a circular shift register, K storage elements, and a code register. The circular shift register having N data samples circularly shifts a first data sample of the N data samples into a data position at a first clock frequency. The N data samples correspond to signal received from one of K satellites in a global positioning system (GPS). The N data samples are loaded into the circular shift register at a second clock frequency. The K storage elements store K code sequences, respectively. Each of the K code sequences has N code samples and includes a first code sample being written at a code position corresponding to the data position at a third clock frequency. The K storage elements correspond to the K satellites. The code register stores the N code samples loaded from one of the K storage elements at a fourth clock frequency. The fourth clock frequency is K times faster than the first clock frequency.

[0028] While this invention has been described with reference to illustrative embodiments, this description is not intended to be construed in a limiting sense. Various modifications of the illustrative embodiments, as well as other embodiments of the invention, which are apparent to persons skilled in the art to which the invention pertains are deemed to lie within the spirit and scope of the invention.

[0029] The A/D converter 130 converts the analog signal from the RF front end circuit 120 into digital data for digital processing in subsequent stages. The A/D converter 130 operates with a sampling frequency at  $16 \cdot f_0$ . The sampling frequency is selected to provide adequate anti-aliasing without incurring complexity and costs to the system 100. A sample-and-hold device (not shown) may be used to hold the analog signal during the A/D conversion. The sample-and-hold device acts like a sampler operating at the sampling frequency. The word length of the A/D converter 130 depends on the characteristics of the signal

and the requirements of the system. In one embodiment, the A/D converter 130 has a word size of one bit. When the A/D converter 130 has a word size of one bit, it can be implemented as a hard limiter using an operational amplifier as a comparator. The output of the comparator is one of two logic levels depending on whether the analog sample is greater or below a predetermined threshold value. The comparator output is the digitized input sample and is latched into a flip-flop clocked at a sampling clock signal. In one embodiment, this sampling clock signal is sixteen times the nominal frequency  $f_0$  of 1.023 MHz. The digitized input samples are then fed to the base-band circuit 140 for base-band processing.

**[0030]** The base-band circuit 140 is the main section to process the digitized signal, or samples, to provide correlation results to the processor 150. The base-band circuit 140 uses a multi-channel multiplexing scheme and a spread spectrum architecture. The base-band circuit 140 has a number of novel features to be described later. These features include efficient processing, simple implementation, and low power. The base-band circuit 140 processes the input signal from a number of satellites in the GPS. In one embodiment, the number of satellites is twelve. The base-band circuit 140 employs a parallel mechanism to process all twelve channels corresponding to the twelve satellites.

**[0031]** The processor 150 is any processor or processing element that is capable of executing instructions and communicating with input/output devices or circuits. The processor 150 generates control information to the base-band circuit 140 and interfaces to input/output devices or elements. The input/output devices or elements may include any suitable input/output. Examples of the input/output devices or elements include user's keyboard, display, serial communication interface, and parallel input/output processor. The processor 150 may include a central processing unit (CPU), a memory, and any appropriate interfacing devices. Examples of the CPU include general-purpose microprocessors with any architecture (e.g., superscalar, vector processor, reduced instruction set computer), micro-controllers, digital signal processors, embedded processors.







mixer circuit to mix the de-spreaded samples with the sine and cosine values provided by a carrier NCO for a selected satellite. For N satellites, N carrier NCO's are used. The Doppler circuit 250 sequences through the N carrier NCO's.

[0038] The epoch processing circuit 260 processes the data at the end of each epoch. At the end of each epoch, the PN code samples are filled with all 1's. The epoch processing circuit 260 sequences through the N satellite channels. The result samples are accumulated or added to provide final result for each satellite. A double-buffered memory scheme is used to allow storing one set of samples in a first memory while a set of results is read out to a second memory. The processor 150 then can access the second memory to retrieve the results for further processing.

[0039] The clock generator 270 generates various clock signals to be used by other circuits in the base-band circuit 140. In one embodiment, the clock generator 270 receives the basic clock signal at 48 times the nominal frequency  $f_0$ . From this basic clock signal, the clock generator 270 generates all or a subset of the following clock signals: a sampling clock signal at  $24*f_0$ , a clock signal at  $16*f_0$ , a clock signal at  $8*f_0$ , a clock signal at  $4*f_0$ , and a clock signal at  $2*f_0$ . The clock generator 270 may be implemented by a number of methods. One method is to use a counter clocked by the basic clock signal and some logic gates. The outputs of the counter are the divide-by-K clock signals that have frequencies of  $24*f_0$ ,  $16*f_0$ ,  $8*f_0$ ,  $4*f_0$ , and  $2*f_0$ . To prevent clock skewing, additional delay elements may be inserted as appropriate.

[0040] Figure 3 is a diagram illustrating the multiplier-free demodulator 220 shown in Figure 2 according to one embodiment of the invention. The demodulator 220 includes a gating circuit 310, a demultiplexer 320, an integrator/decimator 330, a mapper 340, and a reset circuit 350.

[0041] The gating circuit 310 essentially performs a multiplication of the input samples with the sine and cosine values without using an actual multiplier. As discussed earlier, the input samples are one-bit samples clocked at the



a 4-sample interval. The integrator/decimator 330 includes two K-bit counters 332 and 334 to count the number of 1's in the in-phase and quadrature samples from the synchronizers 322 and 324, respectively. The K-bit counters 332 and 334 are reset by a reset signal generated from the reset circuit 350. This reset signal is to start a new integration interval. The K-bit counters 332 and 334 generate in-phase and quadrature decimated samples, respectively, to the mapper 340. K is selected to ensure that the count value can cover the possible range of numbers. Note that the in-phase or quadrature sample is one-bit. Therefore, the possible numbers of bit 1's in the in-phase or quadrature sample in a 4-sample integration interval are 0, 1, 2, 3, and 4. If +1's and -1's are used to encode the integrated samples, these numbers are equivalent to -2, -1, 0, +1, and +2. To represent these numbers, K would have been 3. In other words, the effect of down sampling is that each sample becomes a three-bit sample.

**[0044]** The mapper 340 maps the in-phase and quadrature decimated samples into in-phase and quadrature demodulated samples, respectively. The in-phase and quadrature demodulated samples have L bits where L is less than K. This mapping reduces the number of bits to represent the in-phase and quadrature decimated samples for more efficient processing. This mapping acts like a lower and upper hard limiter on the {0, 1, 2, 3, 4} range to limit the lower value to 1 and the upper value to 3. In other words, 0 and 1 are mapped into 1, 2 is mapped into 2, 3 and 4 are mapped into 3. The mapper 340 includes two combinational circuits 342 and 344 to perform this mapping for the in-phase and quadrature decimated samples, respectively. The three input A, B, and C of the decimated samples are mapped into two outputs  $B_N$  and  $C_N$  as shown in Figure 3. The two-bit in-phase and quadrature demodulated samples are fed to the passive correlator 230 for further processing.

**[0045]** The reset circuit 350 resets the integrator/decimator 330 at the end of each integration interval. The reset circuit 350 includes an M-bit counter 362 and an OR gate 364.

[0046] The M-bit counter 362 is clocked by the true form of the  $8 \cdot f_0$  clock signal and is reset by a system reset signal. The M-bit counter 362 generates a terminal count signal when the maximum count is reached. The OR gate 364 performs an OR operation between the terminal count signal of the M-bit counter 362 and the reset signal. When the reset signal or the terminal count signal is asserted, the reset circuit 350 asserts the reset signal to reset both the K-bit counters 332 and 334 in the integrator/mapper 330. M is selected to correspond to the integration interval. In one embodiment, the integration interval is equivalent to 4-sample interval and M is equal to 2.

[0047] Figure 4 is a diagram illustrating the low power passive correlator 230 shown in Figure 2 according to one embodiment of the invention. The passive correlator 230 includes a load register 410, a circular shift register 420, a correlator circuit 430, a code register 440, N storage elements  $452_1$  to  $452_N$ , and a write circuit 460. Note that for simplicity, only one passive correlator is shown. For completeness, two passive correlators are used to process the in-phase and quadrature components.

[0048] The load register 410 receives the two-bit in-phase and quadrature demodulated samples from the demodulator 220. The load register 410 transfers its contents to the circular shift register 420 at a clock rate equivalent to  $2 \cdot f_0 / M$  where M is the number of demodulated samples to be stored in the load register 410. In one embodiment, the load register 410 has twenty-two elements (or  $M=22$ ) to store a block of 11 samples of two phases. The selection of the number 11 is explained above. The load register 410, therefore, is organized to store a total of forty-four bits. For a nominal value of  $f_0 = 1.023$  MHz, the transfer rate from the load register 410 to the circular shift register 420 is 93 KHz or a period of 10.75  $\mu$ sec.

[0049] The circular shift register 420 circularly shifts a demodulated sample into a data position at the  $2 \cdot f_0$  clock rate. In one embodiment, the shift is





generate the correlation result. The register 540 stores the correlation result at the sampling clock rate.

[0057] Figure 6 is a diagram illustrating the synchronous operation between the circularly shifted data register and the code register shown in Figure 4 according to one embodiment of the invention.

[0058] At time  $t$ , the circular shift register 420 is parallel loaded with 11 pairs of demodulated samples. Each pair includes two phases  $a$  and  $b$ . The 22 samples are  $(a_n, b_n), (a_{n+1}, b_{n+1}), \dots, (a_{n+10}, b_{n+10})$ . At the same time, the code register 440 is loaded with the corresponding 11 pairs of code samples from one of the  $N$  storage elements  $452_1$  to  $452_N$ . The 22 code samples are  $(s_m, t_m), (s_{m+1}, t_{m+1}), \dots, (s_{m+10}, t_{m+10})$ .

[0059] At time  $t+\Delta t$ , the circular shift register 420 circularly shifts the 22 samples so that each sample is shifted to the left and the left most sample  $b_{n+10}$  is shifted to occupy the rightmost position. At the same time, the writing circuit 460 (Figure 4) writes to the rightmost position of the  $N$  storage elements  $452_1$  to  $452_N$ . Then the code register is loaded with one of the  $N$  storage elements  $452_1$  to  $452_N$ . Note that the code register 440 is loaded with contents of all the  $N$  storage elements corresponding to the  $N$  satellites within the  $\Delta t$  time interval. The remaining code samples remain the same.

[0060] At time  $t+2 \Delta t$ , the circular shift register 420 circularly shifts the 22 samples so that each sample is shifted to the left and the left most sample  $a_{n+10}$  is shifted to occupy the rightmost position. At the same time, the writing circuit 460 (Figure 4) writes to the next rightmost position of the  $N$  storage elements  $452_1$  to  $452_N$ . Then the code register is loaded with one of the  $N$  storage elements  $452_1$  to  $452_N$ . The remaining code samples remain the same. The process continues when all  $M$  code samples are written into the  $N$  storage elements  $452_1$  to  $452_N$ . At time  $t+k\Delta t$ ,  $N$  code samples are written into the code position  $k$  while the other code positions contain the same code samples. Thereafter, a new sequence of  $M$





01 (-1)	0 (-1)	01 (+1)
01 (-1)	1 (+1)	11 (-1)
10 (0)	0 (-1)	10 (0)
10 (0)	1 (+1)	10 (0)
11 (+1)	0 (-1)	11 (-1)
11 (+1)	1 (+1)	01 (+1)

**[0068]** Note that the values inside parentheses represent the actual values. Other mappings are possible. The mapping can be implemented by a combinational circuit for the mapper shown in Figure 5.

**[0069]** Figure 8A is a diagram illustrating the pseudo random number (PN) generator and re-tracking circuit 240 shown in Figure 2 according to one embodiment of the invention. The PN generator and re-tracking circuit 240 includes a control circuit 810, N accumulators 820<sub>1</sub> to 820<sub>N</sub>, N increment registers 830<sub>1</sub> to 830<sub>N</sub> and a PN generator 840.

**[0070]** The control circuit 810 generates at least a channel enable signal based on control information from the processor 150 (Figure 1) at the  $8 \cdot f_0$  frequency. For N satellites, the control circuit 810 generates N channel enable signals. The control information includes at least one of channel select information, an initial count, an increment value, and PN command.

**[0071]** Each of the N accumulators 820<sub>1</sub> to 820<sub>N</sub> generates a PN clock signal corresponding to the selected satellite channel based on the increment value. The PN clock signal is used by the PN generator 840. Each of the N accumulators 820<sub>1</sub> to 820<sub>N</sub> is enabled by a corresponding channel enable signal from the control circuit 810.

**[0073]** The PN generator 840 generates N PN code samples to the passive correlator 230 based on the channel select information. As discussed earlier, each of the N satellites has a unique PN code sequence. During normal operation, the PN generator 840 operates at the nominal  $f_0$  frequency. During re-tracking, the PN codes are shifted back and forth based on the individual PN clock signals provided by the N accumulators 820<sub>1</sub> to 820<sub>N</sub>. The PN generator 840 includes N PN code generators 845<sub>1</sub> to 845<sub>N</sub> clocked by the PN clock signals from N accumulator 820<sub>1</sub> to 820<sub>N</sub>, respectively.

**[0074]** Figure 8B is a diagram illustrating the PN code generator 845<sub>k</sub> shown in Figure 8A according to one embodiment of the invention. The PN code generator 845<sub>k</sub> includes a G1 coder 850, a G2 coder 860, an AND gate 865, a tap selector 870, and an exclusive OR gate 875.

**[0075]** The G1 coder 850 generates a G1 code sequence. The G1 coder 850 includes a shift register 852 and an exclusive OR gate 854. The shift register 852 has ten elements and shifts the code bits to the right. The shift register 852 is clocked by the PN clock signal  $k$  from the corresponding accumulator  $820_k$  (Figure 8A). The processor 150 initially loads the shift register 852 with all 1's. The exclusive OR gate 854 is a two-input exclusive OR gate which perform an exclusive OR operation on elements 3 and 10 of the shift register 852. The output of the exclusive OR gate goes back to the input of the shift register 852.

**[0076]** The G2 coder 860 includes a shift register 862 and an exclusive OR gate 864. The shift register 862 has ten elements and shifts the code bits to the right. The shift register 862 is clocked by the PN clock signal  $k$  from the corresponding accumulator 820<sub>k</sub> (Figure 8A). The processor 150 initially loads

the shift register 862 with all 1's. The exclusive OR gate 864 is a six-input exclusive OR gate which perform an exclusive OR operation on elements 2, 3, 6, 8, 9, and 10 of the shift register 862. The output of the exclusive OR gate 864 goes back to the input of the shift register 862.

[0077] The AND gate 865 is a ten-input AND gate which performs an AND operation on all ten elements of the shift register 862. When all the ten elements of the shift register 862 contain all 1's, an epoch event has occurred, i.e., an epoch is ended and a new epoch begins. The output of the AND gate 865, therefore, provides an indication that an epoch has elapsed. This epoch event signal is used by the epoch control circuit in the epoch processing circuit 260 (Figure 6).

**[0078]** The tap selector 870 selects the taps in the shift register 862 of the G2 coder 860 to be used in generating the PN code k out of the PN generator 840 (Figure 8A). The selected taps in the shift register 862 are unique for each satellite. The processor 150 writes the selection to the tap selector 870.

**[0079]** The exclusive OR gate 875 performs an X-OR operation on the output of the G1 coder 850 and the output of the tap selector 870 to generate the PN code k.

**[0080]** Figure 8C is a diagram illustrating the tap selector 870 shown in Figure 8B according to one embodiment of the invention. The tap selector 870 includes a tap register 875, a mask circuit 880, and an exclusive OR gate 890.

**[0081]** The tap register 875 has ten elements corresponding to the ten elements of the shift register 862 in the G2 coder 860. The tap register 875 is written by the processor 150 to select the P taps unique to a satellite. In one embodiment,  $P = 2$ . The mask circuit 880 masks the non-selected taps from the shift register 862 using the tap register 875. The mask circuit 880 includes ten AND gates 8851 to 88510. Each of the AND gate ANDs a cell of the tap register 875 with a corresponding cell of the shift register 862. If any of the cells of the

G2 coder 860 are selected, those cells are tapped into the exclusive OR gate 890. The output of the X-OR gate 890 goes to the exclusive OR gate 875.

[0082] Figure 9 is a diagram illustrating the control circuit 810 for PN shifting technique as it applies to one code NCO generator according to one embodiment of the invention. The control circuit 810 includes a decoder 910, a channel enable register 920, a counter 930, and a logic circuit 940.

[0083] The decoder 910 receives the channel select information from the processor 150 (Figure 1) and generates N decoded signals from the channel select information. For  $N=12$ , the decoder 910 is a 4-to-12 decoder. The channel enable register 920 stores the decoded signals to generate N channel enable signals at a  $8*f_0$  frequency. The loading of the channel enable register 920 is enabled by the logic circuit 940. The channel enable register 920 is asynchronously reset by the logic circuit 940.

[0084] The counter 930 updates a count for the amount of PN shifting required from the initial count at the  $8*f_0$  clock signal. When the count reaches a terminal count, the counter 930 generates a terminal signal to reset the channel enable register 920. In one embodiment, the counter 930 is an 8-bit down counter to count from the initial count to zero, i.e., the terminal count is zero. The processor 150 writes the initial count to the counter 930.

[0085] The logic circuit 940 generates a load signal and a reset signal. The load signal is to load the counter 930 and the channel enable register 920. The reset signal is to reset the channel enable register 920.

[0086] Figure 10 is a diagram illustrating the PN shifting technique as it applies to one code NCO generator according to one embodiment of the invention. The accumulator 820 includes an accumulating register 1010, an adder 1020, and an adder control circuit 1030.

[0087] The accumulating register 1010 stores a NCO value at a current cycle of the  $8*f_0$  clock signal. The NCO value provides the PN clock signal for



1. 1. The first  
 2. 2. The second  
 3. 3. The third  
 4. 4. The fourth  
 5. 5. The fifth  
 6. 6. The sixth  
 7. 7. The seventh  
 8. 8. The eighth  
 9. 9. The ninth  
 10. 10. The tenth  
 11. 11. The eleventh  
 12. 12. The twelfth  
 13. 13. The thirteenth  
 14. 14. The fourteenth  
 15. 15. The fifteenth  
 16. 16. The sixteenth  
 17. 17. The seventeenth  
 18. 18. The eighteenth  
 19. 19. The nineteenth  
 20. 20. The twentieth  
 21. 21. The twenty-first  
 22. 22. The twenty-second  
 23. 23. The twenty-third  
 24. 24. The twenty-fourth  
 25. 25. The twenty-fifth  
 26. 26. The twenty-sixth  
 27. 27. The twenty-seventh  
 28. 28. The twenty-eighth  
 29. 29. The twenty-ninth  
 30. 30. The thirtieth  
 31. 31. The thirty-first  
 32. 32. The thirty-second  
 33. 33. The thirty-third  
 34. 34. The thirty-fourth  
 35. 35. The thirty-fifth  
 36. 36. The thirty-sixth  
 37. 37. The thirty-seventh  
 38. 38. The thirty-eighth  
 39. 39. The thirty-ninth  
 40. 40. The fortieth  
 41. 41. The forty-first  
 42. 42. The forty-second  
 43. 43. The forty-third  
 44. 44. The forty-fourth  
 45. 45. The forty-fifth  
 46. 46. The forty-sixth  
 47. 47. The forty-seventh  
 48. 48. The forty-eighth  
 49. 49. The forty-ninth  
 50. 50. The fiftieth  
 51. 51. The fifty-first  
 52. 52. The fifty-second  
 53. 53. The fifty-third  
 54. 54. The fifty-fourth  
 55. 55. The fifty-fifth  
 56. 56. The fifty-sixth  
 57. 57. The fifty-seventh  
 58. 58. The fifty-eighth  
 59. 59. The fifty-ninth  
 60. 60. The sixtieth  
 61. 61. The sixty-first  
 62. 62. The sixty-second  
 63. 63. The sixty-third  
 64. 64. The sixty-fourth  
 65. 65. The sixty-fifth  
 66. 66. The sixty-sixth  
 67. 67. The sixty-seventh  
 68. 68. The sixty-eighth  
 69. 69. The sixty-ninth  
 70. 70. The seventieth  
 71. 71. The seventy-first  
 72. 72. The seventy-second  
 73. 73. The seventy-third  
 74. 74. The seventy-fourth  
 75. 75. The seventy-fifth  
 76. 76. The seventy-sixth  
 77. 77. The seventy-seventh  
 78. 78. The seventy-eighth  
 79. 79. The seventy-ninth  
 80. 80. The eightieth  
 81. 81. The eighty-first  
 82. 82. The eighty-second  
 83. 83. The eighty-third  
 84. 84. The eighty-fourth  
 85. 85. The eighty-fifth  
 86. 86. The eighty-sixth  
 87. 87. The eighty-seventh  
 88. 88. The eighty-eighth  
 89. 89. The eighty-ninth  
 90. 90. The ninetieth  
 91. 91. The ninety-first  
 92. 92. The ninety-second  
 93. 93. The ninety-third  
 94. 94. The ninety-fourth  
 95. 95. The ninety-fifth  
 96. 96. The ninety-sixth  
 97. 97. The ninety-seventh  
 98. 98. The ninety-eighth  
 99. 99. The ninety-ninth  
 100. 100. The hundredth

$$t = q / \{\Delta M * f_c\} / 2^n = (q/f_g) * (M/\Delta M) \quad (5)$$

$$f_c = 8 \cdot f_0 = 8.184 \text{ MHz}, m = 16, n = 28, M = 2^{25}$$

Number of chips advanced	T ( $\mu$ s)	NCO clock cycles
1	0.977	8
2	1.955	16
3	2.932	24
4	3.910	32
5	4.887	40
5.5	5.376	44

Number of chips slipped	T ( $\mu$ s)	NCO clock cycles
1	1.955	16
2	3.910	32
3	5.065	48

4	7.820	64
5	9.770	80
5.5	10.75	88

[0093] The NCO marching value can be used to advance or slip precisely to within +/- 5.5 chips by counting the number of NCO clock cycles all within less than 11  $\mu$ s. It is also possible to totally stop NCO clock for a number of cycles to compensate for the slippage.

[0094] Figure 11A is a diagram illustrating the Doppler circuit 250 shown in Figure 2 according to one embodiment of the invention. The Doppler circuit 250 includes a carrier NCO 1110, a look up table 1120, two registers 1125 and 1127, and a mixer circuit 1110.

[0095] The carrier NCO generates a carrier NCO value to select sine and cosine values from the look up table 1120. The carrier NCO includes a decoder 1112, N carrier NCO base circuits 1114<sub>1</sub> to 1114<sub>N</sub>, a multiplexer 1116, and a counter 1118. The decoder 1112 generates decoded signals from the channel select information. The decoded signals correspond to the satellite channels. Each of the carrier NCO base circuits 1114<sub>1</sub> to 1114<sub>N</sub> provides a carrier NCO value corresponding to the selected satellite channel. In one embodiment, the carrier NCO value is 3-bit. The multiplexer 1116 selects one of the 3-bit N carrier NCO values based on the select signal generated by the counter 1118. The counter 1118 sequences through the N channels and clocked by the sampling clock signal at  $24 \cdot f_0$  frequency.

[0096] The look up table 1120 generates the coefficients based on the carrier NCO value. The coefficients include the sine and cosine values to be used by the mixer circuit 1130. In one embodiment, the sine and cosine values are stored in the look up table 1120 according to the 3-bit carrier NCO values as follows.

Carrier NCO value	Sine value	Cosine value
000	000 (0)	011 (3)
001	010 (2)	010 (2)
010	011 (3)	000 (0)
011	010 (2)	110 (-2)
100	000 (0)	111 (-3)
101	110 (-2)	110 (-2)
110	111 (-3)	000 (0)
111	110 (-2)	010 (2)

**[0097]** The two registers 1125 and 1127 store the sine and cosine values from the look up table 1120 at the sampling clock signal of  $24 \cdot f_0$  frequency.

**[0098]** The mixer circuit 1130 mixes the demodulated sample from the passive correlator 230 (Figure 2) with the coefficients (e.g., the sine and cosine values) from the look up table 1120 to generate a mixer sample. The mixer sample includes a mixer in-phase sample and a mixer quadrature sample. The mixer circuit 1130 includes mixer in-phase and quadrature circuits 1132 and 1334 to generate the mixer in-phase and quadrature samples, respectively.

**[0099]** Figure 11B is a diagram illustrating the carrier NCO base circuit 1114 shown in Figure 2 according to one embodiment of the invention. The carrier NCO base circuit 1114 includes a carrier increment register 1140, an adder 1150, and a carrier accumulating register 1160.

**[00100]** The carrier increment register 1140 stores a carrier increment value provided by the processor 150 at a  $f_0/4$  frequency. The adder 1150 adds the carrier increment value to the carrier NCO value stored in the accumulating register 1160



to produce a sum. The sum is then stored in the accumulating register 1160. The accumulating register 1160 stores the sum generated by the adder 1150 at a  $f_0/4$  frequency.

[00101] Figure 12 is a diagram illustrating the mixer circuit 1130 shown in Figure 11 according to one embodiment of the invention. The mixer circuit 1130 includes a mixer in-phase circuit 1210 and a mixer quadrature circuit 1220.

[00102] The mixer in-phase circuit 1210 generates an in-phase mixer sample  $I_m$  from the in-phase and quadrature demodulated samples  $I_d$  and  $Q_d$  as follows:

$$I_m = I_d * \cos - Q_d * \sin \quad (6)$$

[00103] The mixer quadrature circuit 1210 generates a quadrature mixer sample  $Q_m$  from the in-phase and quadrature demodulated samples  $I_d$  and  $Q_d$  as follows:

$$Q_m = I_d * \sin + Q_d * \cos \quad (7)$$

[00104] where sin and cos are the sine and cosine values provided by the two registers 1125 and 1127, respectively. The  $I_m$  and  $Q_m$  are the results of complex multiplications between the  $I_d$ ,  $Q_d$  with the sine and cosine values.

[00105] The mixer in-phase circuit 1210 includes two logic circuits 1212 and 1214 and an adder 1216. Each of the logic circuits 1212 and 1214 essentially performs a multiplication between the 6-bit demodulated sample and the sine or cosine value to generate an 8-bit product considering the range of value at the input and output and the coding method used. The multiplexer is a simplified set of logic gates. The adder 1216 adds the two 6-bit products to provide the in-phase mixer sample according to equation (6). The mixer quadrature circuit 1220 includes two logic circuits 1222 and 1224 and an adder 1226. The two logic circuits 1222 and 1224 are the same as the logic circuits 1212 and 1214. The

adder 1226 adds the two 6-bit products to provide the quadrature mixer sample according to equation (7).

[00106] Figure 13 is a diagram illustrating the epoch processing circuit 260 shown in Figure 2, which controls the I and d memory circuits according to one embodiment of the invention. The epoch processing circuit 260 includes in-phase and quadrature memory circuits 1310 and 1320, an epoch control circuit 1330, and a multiplexer 1340.

[00107] Each of the in-phase and quadrature memory circuits 1310 and 1320 accumulates the corresponding mixer samples over an epoch interval. The in-phase and quadrature memory circuits 1310 and 1320 are essentially identical except that the input for the in-phase memory circuit 1310 is the mixer in-phase sample and the input to the quadrature memory circuit 1320 is the mixer quadrature sample. The epoch control circuit 1330 generates an epoch control signal to the in-phase and quadrature memory circuits 1310 and 1320 indicating an end of an epoch. The multiplexer 1340 selects one of the in-phase and quadrature memory circuits 1310 and 1320 to be read by the processor 150.

[00108] Figure 14 is a diagram illustrating the memory circuit 1310 shown in Figure 13 according to one embodiment of the invention. The memory circuit 1310 includes an accumulating memory 1410, four registers 1412, 1414, 1425, and 1435, an address counter 1420, an adder 1430, a buffer memory 1440, a register 1445, and a gating circuit 1450.

[00109] The accumulating memory 1410 stores P sums of the mixer samples during an epoch interval as provided by the epoch control circuit 1330 (Figure 13). The mixer samples arrive at the accumulating memory 1410 at the sampling clock frequency of  $24 \cdot f_0$ , or every 40.72 nsec for a nominal frequency  $f_0$  of 1.023 MHz. Each block of mixer samples includes the complex mixing of the 22-phase block of the input samples and the 22-phase block of the PN code samples. For the entire epoch interval which corresponds to  $1023/11 = 93$  blocks of 22-phase blocks of the input samples, the accumulation essentially adds the 22-

phase result blocks for 93 times. The value of the mixer samples has a range of  $\{-88, +88\}$ . The range of the epoch result is therefore equal to  $\pm 88 \times 93 = \pm 8184$ . This range requires a word size of 14 bits including the sign bit. Each epoch also involves 12 satellite channels. To accumulate 22-blocks for all 12 channels, the total number of epoch values stored in the accumulating memory 1410 is 264. The accumulating memory 1410 is therefore organized as  $512 \times 16$  to accommodate  $264 \times 14$  epoch results. In one embodiment, the accumulating memory 1410 is implemented as a dual-ported memory to allow simultaneous read and write. This allows reading the partial sum from the accumulating memory 1410 and writing the partial sum to the accumulating memory 1410 at the same address at the same time.

[00110] The address counter 1420 generates an address to the accumulating memory 1410 and the buffer memory 1440. The address counter 1420 is clocked by the sampling clock signal of  $24 \times f_0$  frequency. The address counter 1420 sequences through the 12 satellite channels and the 22 phases. Therefore, the address counter 1420 generates the address modulo  $12 \times 22 = 264$ .

[00111] The adder 1430 adds a mixer sample to the sum stored in the accumulating memory 1410. The result of the adder 1430 is written to the accumulating memory 1430. This result is read out in the next cycle to continue accumulating the mixer samples over the epoch interval.

[00112] The buffer memory 1440 stores the P sums transferred from the accumulating memory 1410 at the end of each epoch interval. The contents of the buffer memory 1440 are read by the processor 150 via the multiplexer 1340. In one embodiment, the buffer memory 1440 is a dual-ported memory to allow simultaneous writing and reading.

[00113] The registers 1412, 1414, 1425 and 1435 are clocked by the sampling clock signal at  $24 \times f_0$  frequency to synchronize the latching of the address and data for the accumulating and buffer memories 1410 and 1440.

